



## CO42 Series

400 A (main lugs), 200 A per position, single-phase 120/240 V; multiple position combination with compartment with or without breaker

### Product specifications

- Conductor range: line: dual rated connectors for 1 x 4 AWG–600 kcmil or 2 x 1/0 AWG–250 kcmil, load: 6 AWG–250 kcmil
- Aluminum tunnel type connectors for both load and line sides
- Combination overhead/underground
- Factory pre-bussed from main lugs to each position
- Supplied with hub opening closure plate for underground service
- Internal locking system for covers
- Larger hub opening requires use of 3 in., 3½ in. or 4 in. hubs unless BS052 adaptor plate is used
- Comes complete with blank compartment
- Supplied with screw type rings
- Factory installed 2 pole 10KA OR 22 KA (HI) breakers either an ABB or Siemens
- Factory installed adjustable bracket for field installation of Siemens type QJ(L), QJH(L), QR(L) and QRH(L), SQD type QBL, Eaton type ED
- Conductor kits are available to facilitate field installation of Siemens type QJ(L), QJH(L), QR(L) and QRH(L), SQD type QBL, Eaton type ED(L), refer to page D61
- Weatherproof Type 3R enclosure



	Cat. no.	Type	Description	Position	Dimensions (in.)			Weight Each	
					H	W	D	lb	kg
	Left-hand entry								
	CO42	Combination overhead/underground	2 Gang with blank compartment, Provision for 2 X 2 pole 10 kA rated circuit breaker	2	37 <sup>11</sup> / <sub>16</sub>	26 <sup>3</sup> / <sub>4</sub>	5 <sup>1</sup> / <sub>2</sub>	75	39
	CO42-200	Combination overhead/underground	2 Gang with blank compartment, Comes complete with 2 X 2 pole 200 A 10 kA rated circuit breaker	2	37 <sup>11</sup> / <sub>16</sub>	26 <sup>3</sup> / <sub>4</sub>	5 <sup>1</sup> / <sub>2</sub>	75	39
	CO42-200HI	Combination overhead/underground	2 Gang with blank compartment, Comes complete with 2 X 2 pole 200 A 22 kA rated circuit breaker	2	37 <sup>11</sup> / <sub>16</sub>	26 <sup>3</sup> / <sub>4</sub>	5 <sup>1</sup> / <sub>2</sub>	75	39
	CO43	Combination overhead/underground	3 Gang with blank compartment, Provision for 3 X 2 pole 10 kA rated circuit breaker	3	37 <sup>11</sup> / <sub>16</sub>	35	5 <sup>1</sup> / <sub>2</sub>	100	36.29
	CO43-200	Combination overhead/underground	3 Gang with blank compartment, Comes complete with 3 X 2 pole 200 A 10 kA rated circuit breaker	3	37 <sup>11</sup> / <sub>16</sub>	35	5 <sup>1</sup> / <sub>2</sub>	100	36.29
	CO43-200HI	Combination overhead/underground	3 Gang with blank compartment, Comes complete with 3 X 2 pole 200 A 22 kA rated circuit breaker	3	37 <sup>11</sup> / <sub>16</sub>	35	5 <sup>1</sup> / <sub>2</sub>	100	36.29
	CO44	Combination overhead/underground	4 Gang with blank compartment, Provision for 4 X 2 pole 10 kA rated circuit breaker	4	37 <sup>11</sup> / <sub>16</sub>	43 <sup>3</sup> / <sub>4</sub>	5 <sup>1</sup> / <sub>2</sub>	125	56.70
	CO44-200	Combination overhead/underground	4 Gang with blank compartment, Comes complete with 4 X 2 pole 200 A 10 kA rated circuit breaker	4	37 <sup>11</sup> / <sub>16</sub>	43 <sup>3</sup> / <sub>4</sub>	5 <sup>1</sup> / <sub>2</sub>	125	56.70
	CO44-200HI	Combination overhead/underground	4 Gang with blank compartment, Comes complete with 4 X 2 pole 200 A 22 kA rated circuit breaker	4	37 <sup>11</sup> / <sub>16</sub>	43 <sup>3</sup> / <sub>4</sub>	5 <sup>1</sup> / <sub>2</sub>	125	56.70

Note: Ex. CO42-XXX, suffix (XXX) can be replaced by any of the following breaker amperage options: 100, 125 or 150.

## CO42 Series

400 A (main lugs), 200 A per position, single-phase 120/240 V; multiple position combination with compartment with or without breaker

### Diagrams

